Backplane Technology

TEL 02 9457 6400 sales@backplane.com.au www.backplane.com.au

Backplane Systems Technology Pty Ltd

Proudly Australian-Owned Since 1989







### SPECIAL FEATURES

- IP68 rated medical keyboard
- Adjustable brightness of backlight (TOUCH+)
- Fully washable and disinfectable
- 109 keys incl. num pad and track pad

- Waterproof silicone USB protection cap
- Excellent tactile feeling
- Integrated Clean Mode for cleaning
- Magnetic mounting
- EN60601-1-2 Ed 4 certified

# **SPECIFICATION**

Number of keys: 109 (US-Layout) Interfaces: **USB 2.0** Keyswitch technology: carbon contact Cable length: 15cm

Switching cycles: approx. 2 mill. (per key) Operating temperature: 0°C ~ +55°C

Protection level: IP68 -30°C ~ +70°C Storage temperature: Housing material: silicone Dimensions: 365(L) x 134(W) x 14.2(T) mm

Housing color: white & black Weight: approx. 615g

Backlight: blue color, 5 level adjustable Certification: EN60601-1-2 Ed 4, CE, FCC, RoHS, REACH

> brightness Warranty: 2 years

## ORDER INFORMATION

Cat. No.	Product description	Colour	Layout
KSI-U10210	CLEANTYPE® PRIME TOUCH+	White	US/DE/JP/KR/THAI
KSI-U10211	CLEANTYPE® PRIME TOUCH	White	US/DE/JP/KR/THAI
KSI-U20210	CLEANTYPE® PRIME TOUCH+	Black	US/DE/JP/KR/THAI
KSI-U20211	CLEANTYPE® PRIME TOUCH	Black	US/DE/JP/KR/THAI

Other layouts, configurations and interfaces on request.

Customized key function on request (Firmware update via USB)

GETT Gerätetechnik GmbH

Mittlerer Ring 1 08233 Treuer F-Mail:

+49 37468 660 0

GETT North America LLC Suite 203M 2323 S. Voss Road, Houston, TX 77057

United States of America Tel: +832 649 7822 F-Mail: info@gett-na.com www.gett-na.com GETT Asia Ltd.

Room 806-7. Kowloon Plaza Kowloon, Hong Kong Tel: +852 3461 9789 F-Mail: info@gett-asia.com www.gett-asia.com

#### Backplane Systems Technology Pty Ltd



TEL 02 9457 6400 sales@backplane.com.au www.backplane.com.au

Proudly Australian-Owned Since 1989

## EN60601-1-2 Ed 4 certified

EN 60601-1-2 Ed 4 applies to the basic safety and essential performance of Medical Equipment(ME) equipment and ME systems in the presence of electromagnetic disturbances and to electromagnetic disturbances emitted by ME equipment and ME systems.

## SHORT OPERATING INSTRUCTIONS



Press and hold lock key for 5s to enable Clean Mode. Clean Mode is indicated by breathing backlight.



Adjust backlight level with this button. Five level can be adjusted including off.

## **CLEANING INSTRUCTION**

For further details please refer to below link: http://www.gett-group.com/content/service-cleaning-instructions